

Technical Specification for AC 3 Phase 4 Wire 240V LT CT Solid State (Static) DLMS Compliant Category C1 Four Quadrant Import - Export Energy Meter of 0.5s Accuracy Class and 200/5A CTR

1.0 SCOPE:

This scope covers design, engineering, manufacture, assembly, inspection, testing at manufacturer's works before dispatch, supply and delivery at destination anywhere in the state of West Bengal of **AC 3 Phase 4 Wire 240V LT CT Solid State (Static) DLMS Compliant Category C1 Four Quadrant Import – Export Energy Meter of 0.5s Accuracy Class and 200/5A CTR** with backlit LCD display used for balanced/unbalanced load. The meter shall be capable of recording and displaying different electrical parameters listed elsewhere in the document including Active Energy(kWh), Reactive Energy(kVARh), Apparent Energy (kVAh) etc. over a Power Factor range of Zero Lag to Unity to Zero Lead both in Export & Import mode. Meter shall have facility of recording tamper information & load survey of both export & import phase wise active energy, apparent energy, reactive energy, phase currents, phase voltages & other parameters in nonvolatile memory. These meters shall have communication port for remote meter reading.

It is not the intent to specify completely herein all the details of the design and construction of meter. However the meter shall conform in all respect to high standards of engineering, design and workmanship and shall be capable of performing commercial operation continuously in a manner acceptable to WBSEDCL, who will interpret the meanings of drawings & specification and shall have the right to reject any work or material which in its judgment is not in accordance herewith. The meter shall be complete with all components, accessories necessary for their effective and trouble free operation for the purpose mentioned above. Such components shall be deemed to be within the scope of bidder's supply irrespective of whether those are specifically mentioned or not in this specification or in the commercial order.

2.0 STANDARDS APPLICABLE: Unless specified elsewhere in this specification, the performance & testing of the meters shall conform to the following Indian / International standards, to be read with up-to-date and latest amendments / revisions thereof as on 90 days prior to floating of tender.

Sl. No.	Standard No.	Title
1	IS 14697(1999)	ac Static Transformer Operated Watt hour and Var hour Meters
2	CBIP Report No. 325 & its latest amendments, if any	Specification for AC Static Electrical Energy Meters
3	IS 15959(2011) read with latest amendments, if any	Data Exchange for Electricity Meter - Reading Tariff and Load Control - Companion Specification
4	CBIP Technical Report No. 111	Specification for Common Meter Reading Instrument
5	IS 12346(1999) & its latest amendments, if any	Testing Equipment for AC Electrical Energy Meters

hw
10/1/25

m
10/1/25

AP
10/02/25
10.2.25 10/1/25

al
10.2.25
10/1/25

CLIMATIC CONDITIONS :

The meters to be supplied shall be capable of maintaining required accuracy under hot, tropical and dusty climatic conditions. The meters shall be suitably designed and treated for normal life and satisfactory operation under hot and hazardous tropical climatic conditions and shall be dust and vermin proof. All the parts and surface, which are subject to corrosion, shall either be made of such material or shall be provided with such protective finish which provides suitable protection to them from any injurious effect of excessive humidity.

The meters to be supplied shall be suitable for satisfactory continuous operation under the following tropical conditions.

- Maximum Ambient Air Temperature in shade: 55⁰ C
- Minimum Ambient Air Temperature: (-)10⁰ C
- Maximum Relative Humidity: 95%(non-condensing)
- Minimum Relative Humidity: 10%
- Height above mean sea level: Up to 3000 meters
- Average number of tropical monsoon per annum: 5 months
- Annual Rainfall: 100 mm to 1500 mm
- Maximum Wind Pressure : 150 Kg/Sqm

4.0 SUPPLY SYSTEM :

System	3 Phase 4 Wire
Rated voltage	V _{ref} : 415V (Phase to Phase) or 240V(Phase to Neutral)
Rated Current	I _b : 5A, balanced and unbalanced load I _{max} : 10A CTR: 200/5A
Rated Frequency	50 Hz

5.0 POWER FACTOR RANGE: The meter shall be lag only in import & export mode suitable for full power factor range from zero (lagging) through unity to zero (leading).

6.0 POWER SUPPLY VARIATION: The meter shall be suitable for working with following supply system variations.

System	3 Phase 4 Wire
Specified range of operation	70% to 120% of reference Voltage
Frequency	50Hz \pm 5%

ACCURACY

Class of accuracy of the meter shall be 0.5s as per IS 14697 with latest amendments.

There shall be no drift in accuracy, at least for a period of ten years from the date of supply. In case any drift is noticed which is beyond the permissible limits, the bidder shall have to replace the meter with a new one free of cost.

POWER CONSUMPTION

Voltage Circuit: The active and apparent power consumption in the voltage circuit per phase at reference voltage, reference temperature and reference frequency shall be within 1.5W and 10VA as per IS 14697.

Current Circuit: The apparent power taken by current circuit phase at basic current, reference frequency and reference temperature shall be within 1.0 VA as per IS 14697.

STARTING CURRENT & RUNNING AT NO LOAD

The meter shall start registering energy at 0.1% of basic current at unity power factor and shall be fully functional within five seconds after the rated voltage is applied.

Running at no load: When 70% & 120% of Reference voltage is applied and no current flows in the current circuit, the test output of the meter shall not produce more than one pulse.

10.0 MAXIMUM CONTINUOUS CURRENT: The maximum continuous current in meters shall be the current at which the meter purports to meet the accuracy requirement of the specification. The same is indicated in table in Supply System Clause of this specification.

CONSTRUCTION :

The case, winding, voltage circuit, sealing arrangements, registers, terminal block, terminal cover & name plate etc. shall be in accordance with the relevant standards. The meter shall be compact & reliable in design, easy to transport & immune to vibration & shock involved in the transportation & handling. The construction of the meter shall ensure consistence performance under all conditions especially during heavy rains / very hot weathers. The insulating materials used in the meter shall be non-hygroscopic, non-ageing & have tested quality. The meter shall be sealed in such a way that the internal parts of the meter becomes inaccessible and attempts to open the meter shall result in viable damage to the meter cover i.e. break to open type. This is to be achieved by using continuous Ultrasonic welding on all the four sides of the Meter base and cover or any other technology which is either equally or more efficacious.

The meter shall comply latest technology such as Microcircuit or Application Specific Integrated Circuit (ASIC) to ensure reliable performance. The mounting of the components on the PCB shall compulsorily be Surface Mounted Technology (SMT) type. Power supply component may be of PTH type. The electronic components used in the meter shall be of high quality and there shall be no drift in the accuracy of the meter for at least ten years. The circuitry of the meter shall be compatible with 16 Bit (or better) ASIC with compatible processor and meter shall be based on Digital measuring and sampling technique.

The meter shall be housed in a safe, high grade, unbreakable, fire resistant, UV stabilized, virgin Polycarbonate casing of projection mounting type. The meter cover shall be

10/12/15

10/12/15

10/12/15

10-2-25/10/12

10/12/15

10/12/15

transparent / translucent. But the viewing portion shall be transparent for easy reading of displayed parameters, and observation of operation indicators. The meter base may not be transparent, but it shall not be black in color. The meter casing shall not change in shape, color, size and dimensions when subjected to 72 hrs on UV test as per ASTM D 53. It shall withstand 650 deg. C. glow wire test and heat deflection test as per ISO 75 or as per IEC 60068 -2-5.

In addition to the above, the meter cover shall be sealable to the meter base with at least 2 nos. bar coded seals bearing the identification marks of the Manufacturer. Suitable arrangement shall be made for fitting/fixing of utility seal at two sides of meter terminal cover in such a manner that any access to the terminal cannot be made possible without removing the seal. There shall also be provision for sealing at the optical port.

The polycarbonate material of only the following manufacturers shall be used:

G.E. PLASTIC : LEXAN 943A or equivalent like 943, 123R, 143 for meter cover & terminal cover / LEXAN 503R or equivalent like 500, 143R, 500R for meter base and terminal block.

BAYER : Grade corresponding to above

DOW Chemical : --do--

MITSUBISHI : --do--

TEJIN : --do--

DUPONT : --do--

METER CASE AND COVER :

In case, ultrasonic welding using plate / strip is used, the material of plate / strip shall be same as that of cover and base and the strip. The manufacturer's logo shall be embossed on the strip / plate. The material of the meter body (case and cover) shall be of Engineering Plastic.

The meter cover shall be fixed to the meter base (case) with Unidirectional Screws, so that the same cannot be opened by use of screwdrivers. These unidirectional screws shall be covered with transparent caps (not required for screw less design), ultrasonically welded with the meter body and the screw covers shall be embedded in the meter body in a groove. The meter shall withstand external magnetic influence as per latest amendments of CBIP Technical Report No.325 including 0.2T AC Magnet, 0.5 T Permanent magnet.

TERMINAL BLOCK AND COVER:

The terminals may be grouped in a terminal block having adequate insulating properties and mechanical strength. The terminal block shall be made from best quality non-hygroscopic, flame retardant material (capable of passing the flammability tests) with nickel plated brass inserts / alloy inserts for connecting terminals. It shall be rigidly fixed to the base of the meter so that it cannot be separated from the meter base without

[Handwritten signatures and dates are present at the bottom of the page, including dates like 10/12/25 and 10/12/25.]

breaking either the meter base or the terminal block and this fixing arrangement shall be in parallel to the meter base in such a way that it cannot be viewed or approached from any part of the meter without breaking the meter.

The terminals in the terminal block shall be of adequate length in order to have proper grip of conductor. The screws shall have thread size not less than M4 and head having 6 mm. Diameters. The screws shall not have pointed ends at the end of threads. All terminals and connecting screws and washers shall be of tinned / nickel plated brass material. The terminal shall withstand glow wire test at $960 \pm 15^\circ\text{C}$ and the terminal shall withstand at least 135°C as per IS.

The internal diameter of terminal hole shall be minimum 5.5 mm and center to center distance is 13 mm. The holes in the insulating material shall be of sufficient size to accommodate the insulation of conductor also.

The terminal cover shall be transparent re-enforced Polycarbonate, Engineering Plastic with minimum thickness 2.0 mm and the terminal cover shall be of extended type completely covering the terminal block and fixing holes. The space inside the terminal cover shall be sufficient to accommodate adequate length of external cables.


the meter shall be capable of providing phase to neutral protection up to 433 V for 1(one) hours.


MARKING OF THE METER :


The marking on the meter shall be in accordance with relevant clauses of IS 14697. The basic marking on the meter nameplate shall be as follows. All other markings as per IS shall also be there.


Manufacturer's name & trade mark
Type Designation
No. of phases & wires
Serial number (Size not less than 5mm)
Month & year of manufacture
Reference Voltage
Rated Secondary Current (I_b)
Rated Maximum Current (I_{max})
CT Ratio (200/5A)
Operating Frequency
Principal unit(s) of measurement
Meter Constant (imp/kWh)
Class index of meter
"Property of WBSEDCL"
Purchase Order No. & Date
Guarantee (Guaranteed for a period of 5 ½ years from the date of delivery)


10/12/25


10/12/25


10/12/25


10/12/25


10/12/25

BIS marking

Place of manufacture

Barcode for meter serial no. in alpha numeric form, date of manufacture, current rating of the meter and PO reference, readable by single layer barcode/QR code reader.

The reference temperature if different from 27 °C.

Marking on Meter (Import/Export)

The sign of Double Square for insulating encased meters.

Firmware version

15.0 CONNECTION DIAGRAM AND TERMINAL MARKING: Every meter shall be indelibly marked with a diagram of connection. For this poly phase meters, this diagram shall also show the phase sequence for which the meter is intended. It is permissible to indicate the connection diagram by an identification figure in accordance with relevant standards. The marking of meter terminals shall appear on this diagram.

DISPLAY OF MEASURED VALUES :

The meter shall have alphanumeric display with at least 7 full digit with LCD backlit display, having minimum character height of 10 mm. The data shall be stored in nonvolatile memory. The non-volatile memory shall retain data for a period of not less than 10 years under unpowered condition. Battery back-up memory will not be considered as NVM.

It shall be possible to easily identify the single or multiple displayed parameters through symbols / legend on the meter display itself or through display annunciation which shall be self explanatory and symmetric.

In addition to provide Serial Number of the meter on the display plate, the meter serial no. shall also be programmed into meter memory for identification through communication port for CMRI / laptop / meter reading printout.

Visibility of display in poor light conditions is an important criterion. STN or TN or any better type of advanced LCD to be used. Proper legends for the displayed parameters to be provided (Factory programmable). Back lit provided for clear visibility shall be uniform throughout all part of the LCD.

The meters shall have auto-display mode for pre-selected parameters. Push-Button mode of display shall display all parameters and it shall have priority over auto mode. The meter shall give clear message on display to indicate that the meter has experienced tampers and the nature of tamper, last occurrence and last restoration, if the Last tamper status is not restored, then meter will indicate, last restoration and last occurrence.

Connection check, Phase sequence and self diagnostic shall give clear message on display. The meter shall have a test output (blinking LED) accessible from the front and be capable of being monitored with suitable testing equipment. The operation indicator must be visible from the front. Test output device shall be provided in the form of one common LED for active and reactive energy with the provision of selecting the parameter being tested (separate LED may also be used with proper separation).

DISPLAY SEQUENCE: The meter shall display the required parameters in two different modes as follows. Display sequence for both auto and Push button must be maintained, no interchange in sequence or display parameter will be accepted. All the display shall have proper legend to identify the same.

Auto Display Mode: The following parameters shall be displayed in auto cycle mode, in the following sequence.

- LCD test
- Meter serial number
- Real Date (dd mm yy)
- Real Time (hh mm ss)
- Cumulative Active Import Energy
- Cumulative Active Export Energy
- Cumulative Apparent Import Energy
- Cumulative Apparent Export Energy
- Maximum Demand in Active Import
- Maximum Demand in Active Export
- Instantaneous Average Power Factor
- TOD Active Energy Import
- TOD Active Energy Export
- TOD Apparent Energy while Active Import
- TOD Apparent Energy while Active Export
- R Phase to Neutral Voltage
- Y Phase to Neutral Voltage
- B Phase to Neutral Voltage
- R Phase Current
- Y Phase Current
- B Phase Current
- Cumulative Tamper Count
- Cumulative Power OFF Hours
- Power OFF Hours of present month
- Cumulative Billing Count

Push Button mode: The following parameters shall be displayed on pressing the push button. The meter display should return to Auto Display mode (mentioned above) if the 'push button' is not operated approx. more than 6 seconds.

- LCD test
- Meter serial number
- Real Date (dd mm yy)
- Real Time (hh mm ss)
- Rising Demand (both import and export) in KVA with elapsed time.
(Should get refreshed without delay)
- Voltage Phase Sequence
- Current Phase Sequence

Specification for 3ph 4wire 240V LT CT Import-Export meter of Class 0.5S accuracy

hw
10/12

M
10/12

SP
10/12

10.12.15

10/12/15

Cumulative Active Import Energy
 Cumulative Active Export Energy
 Cumulative Apparent Import Energy
 Cumulative Apparent Export Energy
 Maximum Demand in Active Import with date & time
 Maximum Demand in Active Export with date & time
 Maximum Apparent Demand While Active Import with date & time
 Maximum Apparent Demand While Active Export with date & time
 Cumulative Reactive Import while Active Import Energy
 Cumulative Reactive Import while Active Export Energy
 Cumulative Reactive Export while Active Import Energy
 Cumulative Reactive Export while Active Export Energy
 R Phase to Neutral Voltage
 Y Phase to Neutral Voltage
 B Phase to Neutral Voltage
 R Phase Current
 Y Phase Current
 B Phase Current
 Neutral Current
 Inst. Power Factor – Phase Wise
 Instantaneous Average Power Factor
 Instantaneous Active Power (Export or Import with proper sign/indication)
 Instantaneous Apparent Power (Export or Import with proper sign/indication)
 TOD Active Energy Import
 TOD Active Energy Export
 TOD Apparent Energy while Active Import
 TOD Apparent Energy while Active Export
 History 1 TOD wise Active import energy
 History 1 TOD wise Active export energy
 History 1 TOD wise Apparent import Energy
 History 1 TOD wise Apparent export Energy
 History 1 TOD wise Maximum Demand in Apparent while Active import
 History 1 Maximum demand in Apparent while Active import Occurrence Time and Date
 History 1 TOD wise Maximum Demand in Apparent while Active export
 History 1 Maximum demand in Apparent while Active export Occurrence Time and Date
 History 1 Maximum demand in Active import
 History 1 Maximum demand in Active import Occurrence Time and Date
 History 1 Maximum demand in Active export
 History 1 Maximum demand in Active export Occurrence Time and Date
 Phase wise % Voltage THD
 Phase wise % Current THD
 Cover Open Information with date and time
 Cumulative Power OFF Hours in hour: minute from the date of manufacturing.
 Power OFF Hours of present month
 Average Power Factor (Previous Month)

10/12/25

10/12/25

10/12/25

10.2.15

10/12/25

10/12/25

Avg. Load Factor (Previous Month)
Instantaneous Frequency
Present Tamper Status (PT/CT/Others)
Last Occurrence with Date & Time
Last Restoration with Date & time
Cumulative Tamper Count

High resolution display both Import & Export for kWh, kVAh (Lag + Lead) and kVAh (minimum 2+4)

High resolution display both for Import & Export for kWh, Phase wise (minimum 2+4)

Connection check(when all phase are forward or reverse)
Self Diagnosis
Battery Status

Power OFF Mode Display:

Meter Serial No.
Real Time
Date
Cumulative Active Import Energy
Cumulative Active Export Energy
History 1 TOD wise Active import energy
History 1 TOD wise Active export energy
History 1 TOD wise Apparent import Energy
History 1 TOD wise Apparent export Energy
History 1 TOD wise Maximum Demand in Apparent while Active import
History 1 TOD wise Maximum Demand in Apparent while Active export
Cumulative Billing Count
Cumulative Tamper Count
Cover Open Information with date and time

Display for Auto and manual mode must be listed by two headers:

"Auto Display Mode"
"Push Button Mode"

Display: Other requirements:

Each parameter shall be on meter display for 30 sec and the time gap between two auto display cycles shall be 20 sec.

hms
10/12

10/2/25

10/2/25

10.2.25

10/2/25

The register shall be able to record and display starting from zero, for a minimum of 1500 hours, the energy corresponding to rated maximum current at reference voltage and unity power factor. The register shall not roll over in between this duration.

High resolution display can be given in separate mode.

No decimal is required for main kWh, kVAh, kVarh (lag & lead) display.

Push button mechanism shall be of high quality and shall provide trouble free service for a long span of time.

Up and Down scrolling facility of display parameters shall be there for Push Button Mode.

18.0 For OBIS Codes of parameters, specified in this Technical Specification, other applicable standards may be referred, in case those are not available in the standards referred in this document.

ANTI TAMPER FEATURES : The meter shall have the following anti-tamper features:

The meter shall be capable of recording energy correctly at Import as well as Export mode. If any phase current flows in forward direction, the meter shall register energy in phase-wise Import counter and if phase current flows in reverse direction, it shall register energy in Export counter. Simultaneous Import & Export in different phases shall be allowed and this will not be treated as any Tamper event.

The meter shall work correctly irrespective of phase sequence of supply. (There must be an indication in display & down loaded data).

The meter shall work correctly even in absence of neutral. For reference voltage V_{ref} between 70% to 120 %, accuracy must be maintained as specified in relevant IS.

Meter shall record energy within maximum error of $\pm 4\%$ on injection of DC, pulsating DC (7-10 Hz), chopped AC in Neutral along with logging of ND tamper. In case tamper event is not logged, i.e, meters are immune to neutral disturbance, accuracy of the meters must not be affected. Maximum chopping for AC injection will be 25% to 30% at peak end.

The registration shall not be affected more than + 4% if high frequency (55Hz to 100Hz) or low frequency (45Hz to 30 Hz) AC signal w.r.t. earth is applied to the meter neutral. Meters which are immune or will maintain better accuracy, will be preferred.

The meter shall be immune to Electro Static Discharge or Sparks of 35 KV (approx) induced by using frequency-generating devices having very high output voltage.

Tests in this respect will be conducted by using commonly available devices and during spark discharge test, spark will be applied directly at all vulnerable points of the meter for a period of 10 minutes (at an interval of 1minute (approx) between two consecutive strokes) and meter shall maintain accuracy after the test under this condition. Accuracy will be checked during and after application of spark discharge Test. Meter shall record correctly within the specified limits of errors. Beyond 35 KV the meter shall record tamper if not immune.

- Power failure (Tamper count not to be increased) - as per tamper logic
- Invalid Voltage - as per tamper logic
- Missing Potential (phase wise) —as per tamper logic
- High Voltage – as per tamper logic
- Voltage Unbalance – as per tamper logic
- CT Open - as per tamper logic
- CT Bypass/ CT Short - as per tamper logic
- Over Current - as per tamper logic
- Neutral Disturbances (If it is logged) - as per tamper logic
- Magnetic Disturbances - as per tamper logic
- The meter shall record and display total energy including Harmonic energy in following conditions.

(a) Voltage and current both in phase
(b) Voltage and current both out phase
(c) Voltage in phase and current out phase
(d) Voltage out phase and current in phase

- Ref. Voltage, 0.5 I_{max} and UPF with
 - 10 % 5th harmonics in voltage and 40% 5th harmonics in current.

② Phase wise voltage THD when crosses threshold value of 8%

② Phase wise current THD when crosses threshold value of 8%

abnormalities. More than one tamper CT related/ PT related/ others may be logged at a
Specification for 3ph 4wire 240V LT CT Import-Export meter of Class 0.5S accuracy
Page 11 of 33

time. A minimum of 300 events (one event means either occurrence or restoration) of all types of tamper with date & time stamping shall be available in meter memory compartment wise. The logging will be on FIFO basis. The events will be divided into three compartments like *CT related (148 Events)*, *PT related (88 Events)* and *others (64 Events)*.

Meter shall have a continuous and clear indication in its display if top cover is removed / opened and even re-fixed (non rollover) and only cover open must be logged in BCS without any restoration. COVER OPEN tamper is to be displayed after every parameter displayed in Auto Display Mode.

Measurement of Harmonics: The meter shall be capable of measuring fundamental energy as well total energy i.e., fundamental plus harmonics energy. All energy measurement in KWh and KVARh will be done in fundamental frequency and it will be made available in all communicative channels like Meter Display, BCS, communication through MODEM, ASCII conversion. The energy parameters (KWh & KVARh) at total frequency(fundamental+harmonic) to be available in BCS only.

RESETTING OF MAX. DEMAND

The meter shall be capable of recording the Apparent MD both in import & export mode with integration period of 15 minutes (programmable). MD reset shall be through each of the three means:

Automatic resetting at preset date & time (at present it will be at 00.00 hrs of the first day of the month)

Manually i.e., by push button.

Through authenticated command from MRI or through Remote Communication.

The means by which the reset has been done shall be made available to downloaded data. Facility to invoke any of the above through authenticated MRI command shall be provided at BCS. MD reset button shall have proper sealing arrangement.

There shall be separate Push button for scrolling display (up and down) and MD reset. If only two Push buttons are used minimum 90 sec pressing is required for MD reset.

LOAD SURVEY: The meter shall be capable of recording load survey for the following parameters for a period of minimum 45 days - subject to availability of all parameters listed below with 15 minutes integration period.

Energy in kWh & kVAh, (Import & Export mode shall be shown clearly)

Demand in kVA and kW, (Import & Export mode shall be shown clearly)

Current – phase-wise

Voltage – phase-wise

Phase wise Power Factor

22.0 The NVM shall not require any additional battery backup to retain the data in case of power failure, for up to 10 years and the data storage shall be independent of battery backup unit.

Handwritten signature and date: 10/2/25

Handwritten signature and date: 10/2/25

Handwritten signature and date: 10/2/25

Handwritten signature and date: 10/2/25

Handwritten signature and date: 10/2/25

The life of the RTC battery in circuit condition shall be minimum 10 years in case of power failure. It shall be possible to transfer this data to base computer software through MRI/Laptop or RMR. The Load Survey data so obtained shall be displayed in both graphical & numeric form in the BCS. The BCS with all details is to be provided by the supplier at no extra cost.

23.0 TIME OF DAY FACILITIES : For both import & export mode the meter shall have facilities to record Active, Apparent Energies and MD in at least 8 time zones with 8 tariff. The time zones shall be user programmable through authenticated MRI/Laptop/RMR command. Necessary software for the same is to be provided by the bidder. At present TOD timings will be programmable as follows:

23.1 TOD 1: 06:00 Hrs to 17:00 Hrs.

23.2 TOD 2: 17:00 Hrs to 23:00 Hrs.

23.3 TOD 3: 23:00 Hrs to 06:00 Hrs.

24.0 METER READING DURING POWER OFF: It shall be possible to read the meter-display visually and with MRI/Lap top in absence of input voltages with the help of internal battery backup. In case of external battery the arrangements shall be such that hands free operation is possible. In case of external battery 10 years guarantee must be given for external battery/power pack. Separate battery shall be used for this purpose (Not RTC or processor battery). In case of Lithium battery rating shall be at least 500mAh.

25.0 SELF DIAGNOSTIC FEATURES: The meter shall be capable of performing complete self-diagnostic check to monitor the circuits for any malfunctioning to ensure integrity of data memory location all the time. If possible, the details of malfunctioning shall be recorded in the meter memory. The bidder shall furnish the details of self-diagnostic capability feature, viz Memory status (NVM) and Battery status, RTC Status etc. and it shall be in display.

26.0 IMMUNITY TO ELECTRO MAGNETIC DISTURBANCE: The meter shall be designed in such a way so that external electromagnetic field or electrostatic discharges do not influence the performance of the meter as per IS 14697.

27.0 TECHNICAL SUPPORT, MANUALS & TRAINING: Extensive technical support, detailed technical literature (shall supply with each meter at the time of packing) & training is to be provided by the manufacturer. Supply of External Battery Packs if required to be provided by the manufacturer and shall be clearly offered in their bids.

INFLUENCE QUANTITIES : The meter shall work satisfactory with guaranteed accuracy as per limit provided in IS: 14697 (clause No.9.2.1 and 11.2) under presence of the following quantities:

Electromagnetic field

Specification for 3ph 4wire 240V LT CT Import-Export meter of Class 0.5S accuracy

Page 13 of 33

10/12/25

10/12/25

10/12/25

10/12/25

10.2.25

10/12/25

External magnetic field

Radio frequency interference

Vibration

Voltage variation (70% - 120% of $V_{ref.}$) in 0.5 lag and upf both in 5% and 100% of I_b

Frequency variation (+/-) 5% of 50 Hz in 0.5 lag and upf both in 5% and 100% of I_b

COMMUNICATION CAPABILITY:

The meter shall be provided with two ports for communication of the measured and stored data. Additional RS232 port in the form of RJ45/RJ11 shall be used for remote access through suitable Modem and shall be housed inside the meter terminal cover so that it can't be accessed without opening the sealed terminal cover.

The other one shall be an Optical port complying with hardware specifications detailed in IEC-62056-21. This Optical port shall be provided with proper sealing arrangement so that

its cover can't be opened without breaking its seal. This shall be used for local data downloading through a DLMS compliant HHU or direct through BCS.

Both ports shall support the default and minimum baud rate of 9600 bps.

Optical Cord (for connecting Optical Port of Meter to PC) must be having USB connector.

Data downloading time from meter to HHU/PC shall be within 2 minutes for meter data (without load survey) and within 6 minutes for meter data (with load survey).

The stored data in the meter shall be available through CMRI even when the display of the meter is not available.

No alteration shall be possible without authenticated commands set by the BCS after scheduling the meters. Moreover, no alternation shall be possible using CMRI only, i.e. the control has to be with the BCS as well.

Date in the meter shall be reset only through commands from the CMRI or Laptop. Correction of RTC time, change of TOD timings etc. shall be done through CMRI or Laptop utilizing authenticated command set by BCS.

Billing parameters shall be factory programmable.

The BCS shall have multi-level password for data protection & security.

Bidder has to submit CMRI software (.exe format) also at the time of sample meter testing.

BASE COMPUTER SYSTEM & SOFTWARE REQUIREMENTS:

The Common Meter Reading Instrument (CMRI) shall be loaded with user-friendly software (MS-DOS 5.0 or higher version compatible) for reading and/or downloading meter data.

Windows (Windows 7.0 or higher version) based Base Computer Software (BCS) shall be provided for receiving data from CMRI and downloading instructions from BCS to CMRI.

The data stored in the meters memory including defrauded energy shall be available on the BCS.

Six no. of BCS shall be provided for downloading data from CMRI and for authenticated command from Laptop or for programming CMRI for any transaction.

The BCS shall have facility to convert meter reading data into user definable ASCII file format so that it can be integrated with the billing system or any other third party software. The user shall have the flexibility to select the parameters to be converted into ASCII file.

All the data available in the meter including energy, MD etc. with date and time stamp, new TOD time zones and historical data shall be available in BCS after downloading.

The bidder shall supply the necessary CMRI software during sample meter testing.

The bidder has to supply the meter reading protocol and API free of cost. The bidder shall indicate the relevant standard to which the protocol is compliant.

Transfer of data from the meter to CMRI & then to the BCS shall be easily executed.

Any change or up gradation of CMRI software or BCS in future, required for any reason, has to be done by the supplier at his own cost.

hw
10/2/25

AP
10/2/25

10-2-25

10/2/25

10/2/25

10/2/25

10/2/25

10/2/25

The same software shall be capable of preparing CMRI to read the meter information or to reconfigure the meter for change of TOD timings and / or time setting of the meter etc. The exhaustive online help shall be available with the software so that user can use all the features of the software by just reading the help contents.

In BCS twelve months' data for kWh, kVAh, MD in kW & kVA (total & TOD wise), average load factor, average power factor for both import & export must be available.

GENERAL REQUIREMENTS:

GUARANTEED TECHNICAL PARTICULARS: The bidder shall furnish all the necessary information as desired in the Schedule of Guaranteed Technical Particulars and data, appended with this Specification. If the bidder desires to furnish any other information in addition to the details as asked for, the same may be furnished against the last item of this Annexure- I.

TECHNICAL DEVIATIONS: Any deviation in Technical Specification as specified in the Specification shall be specifically and clearly indicated in the Schedule of deviation format.

Inspection & Testing:

The meters manufactured as per requisite technical specification along with accepted changes recorded in minutes of pre-bid meeting, shall be subject to tests as per relevant Indian Standards.

No change/ deviation/ modification in the technical specification of the meters offered for inspection & testing in respect to the approved sample meters shall be entertained.

BCS and CMRI software version shall be the same as accepted during approval of the related sample meter. In case any change in BCS and/or CMRI software is felt necessary by the supplier, the Chief Engineer(DTD) shall have to be approached in writing for his approval elaborately clarifying the necessity prior to commencement of inspection. The deviation(s) shall be accepted if and only if the Chief Engineer(DTD) approves the proposed deviation(s).

Stage Inspection: Stage Inspection, if required may be conducted at manufacturers' works. For this, the supplier must give prior intimation at least 15(fifteen) days before final calibration (with RTC reset). The supplier shall extend all facilities for such inspection and testing for which no extra cost shall be charged and the physical inspection report, containing observation against components, raw materials, display modules, push button, nameplate etc. shall have to be signed jointly. Otherwise offer for final inspection will not be accepted.

[Handwritten signatures and dates: 10/2/25, 10/2/25, 10/2/25]

Routine Test: Routine Tests as per relevant Indian Standards and requisite technical specification shall be conducted for each & every meter after its production.

Lot Acceptance Test:

The supplier shall give prior intimation about the readiness of the meters at the works for inspection and testing at least 15 (fifteen) days before their proposed inspection schedule. The supplier shall extend all facilities for such inspection and testing for which no extra cost shall be charged and the inspection report shall have to be signed jointly. Otherwise the offered lot(s) shall be treated as cancelled.

While offering inspection and testing, one hard copy & one soft copy of the test reports indicating test results of each meter of the offered lot containing its sequential meter serial no. and the serial no. of the two no. of body seals shall be submitted to the Office of the Chief Engineer (DTD), WBSEDCL, Abhikshan, Sector - V, Salt Lake City, Kolkata - 700091 with copies to the Office of the Chief Engineer (P&C), WBSEDCL. Otherwise inspection offer will not be considered.

However, WBSEDCL reserves the right to depute their Engineers for carrying out inspection and testing on the offered lot as per relevant Indian Standards and requisite technical specification, already notified and also reserves the right to reject either raw materials or finished products found to be not conforming to the requisite technical specifications and/or relevant Indian Standards.

The Engineers of WBSEDCL shall witness the various quality control measures adopted in production line and satisfy themselves about the same. They shall also inspect the protocol for maintaining the accuracy of the meter testing equipment at the testing laboratory of the manufacturer with reference to the standard. The instruments and equipment required for inspection & testing shall have valid calibration certificates as specified in relevant clause of this order.

Physical examination of the meters on minimum 5% of offered quantity will be carried out. If during physical inspection anomaly is found in more than 2% of the offered quantity, no further test will be carried out and offered quantity will be rejected.

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10.2.25

[Handwritten signature]
10/04/25

After satisfactory result in physical examination, lot acceptance tests shall be carried out by the representatives of WBSEDCL at the works of the manufacturer as stated hereunder:

The maximum no. of meters in each lot: 1000

No. of meters to be selected at random from the lot : 32

After selection of sample meters, the following tests shall be carried out on all the 32 no. of meters selected at random.

High Voltage test

Insulation Resistance test

Test of Protection for withstanding 433V between Phase & Neutral for 1(one) hour

Test of Starting Current at 0.1% Ib at UPF

Test of No-Load condition: As per 14697 with latest amendments.

In the above tests, if the number of defective meters is at most one, the lot shall be considered conforming to the tests.

If the number of defective meters is more than three, the lot shall be outright rejected.

However, if the number of defective meters is within three, while the lot shall be considered not conforming to the tests, further sampling from the lot at random shall be made. If the number of defective meters from two such samples (i.e. from 64 meters) is less than four only then the lot shall be considered as conforming to the test.

Further testing for 8 number of meters, selected from 32 number of sample meters will be carried out as follows:

Limits of error on all the same 8 no. of sample meters in import & export mode for both active & reactive energy for balanced & unbalanced loads as per IS 14697(2020).

[Handwritten signatures and dates]
10/2/25
10/2/25
10/2/25
10/2/25
10/2/25
10/2/25

Test of the Meter Constant and Meter Dial as per technical specification at 200% I basic, Power Factor 0.866(lag & lead) for exclusive import, exclusive export and combined import-export mode.

Power consumption on Voltage Circuit (through power analyzer) and Current Circuit.

Further testing of 3 number of sample meters will be carried out as follows:

- 31.3.6.12.1 Repeatability of Error Test for both import & export mode as per IS 14697(1999).
- 31.3.6.12.2 If any of the meters fails on any of the above tests, the lot will be rejected.

Further testing for 1 number of sample meter will be carried out as follows:

- 31.3.6.13.1 Tamper & Fraud protection (Anti-tamper feature) as per relevant clause of the specification.

If the meter fails on any of the above tests, the lot will be rejected.

Few mention-worthy relevant points regarding tamper testing :

AC Chopped signal may be generated through Regulator or Dimmer 31.3.6.15.2

In Discharge Test, meter performance will be checked applying 35 KV spark

Provision must be there for tamper logging in BCS in case the spark exceeds 35 KV

In BCS , average PF & LF, kWh, kVAh, MD in kW & kVA, TOD-wise kWh and kVAh must be made available for last twelve (12) months

In Magnetic Tamper Test, magnetic influence shall be checked at 10mT AC, 0.27T DC, 0.2T AC and 0.5T Permanent Magnet also magnetic influences as per CBIP 325 . Facility to measure the capacity of these magnetic fields must be available at manufacturers' premises and must be calibrated from any NABL accredited laboratory.

Dry Heat Test:

Facilities or arrangement for conducting ageing test shall be available with the manufacturer.

Dry heat test as per clause 12.6.1 of IS: 14697(1999) – At least one sample selected from any lot of the meters offered for first inspection will be sealed by the inspecting authority of WBSEDCL and handed over to the supplier for

hms
14/12

10/12/25

10/12/25

10.12.25

10/12/25

testing at NABL accredited laboratory. In the test report, meter serial no. & meter body seal nos. are to be mentioned.

Test result must be submitted within 30 days after selecting the meter at the manufacturer's works. If not submitted within the stipulated time frame, no further offer for inspection will be accepted.

If the meter fails at dry heat tests, the particularly delivered lot will not be accepted and the delivered meters are to be taken back by the supplier at their own cost from different site offices within 30 days from the date of receipt of intimation in this regard. Only after withdrawal of the delivered meters, further inspection shall be conducted against subsequent offered lot of meters.

If the meter, selected during inspection at first lot of meters, fails in dry heat test, the same test is to be conducted for the consecutive offered lots of meters following the above procedure, unless satisfactory performance on above test is observed.

Reoffer for Inspection :

Materials shall have to be reoffered for the following cases:

Failure to present the offered materials during inspection & testing, i.e, in case of fake offer.

Failure of any particular lot of offered materials in two consecutive inspections.

Inspected materials not delivered within one month after the stipulated period specified in the order without any valid reason. [The dispatch clearance already issued against the said lot shall be considered to be withdrawn]

The date of reoffer shall be the date of submission of reoffer along with WTC & copy of DCR.

Retesting Charge : Retesting fee for carrying out inspection of the lot of materials after reoffer shall be charged as per existing rate.

Test Facilities: The tests for equipment / instrument shall be carried out as per relevant Standards and test certificates shall be furnished for scrutiny. The Bidder shall indicate the details of the equipment available with him for carrying out the various tests as per relevant Standards. The bidder shall indicate the sources of all equipments / instruments.

The standard meters used for conducting tests shall be calibrated periodically at any NABL Accredited Test Laboratories and test certificates shall be available at Works for verification by purchasers' representative.

The manufacturer shall have at least the following testing facilities to ensure accurate calibration:-

AC high voltage test

Insulation test
Test of no load condition
Test of Starting condition
Test on Limits of error (Automatic Testing facility with ICT)
Power consumption in voltage and current circuit
Test of Repeatability of error
Test of meter constant
Test of magnetic influence (As per CBIP 325 with latest amendments & 0.2T AC & DC magnet and 0.5T Permanent Magnet)

SUBMISSION OF SAMPLE METER:

The bidder will submit his sample Meters in sealed casing / cartoon along with relevant Meter documents (As per Annexure-IV), on any working day as per schedule of submission specified in the related Tender Document, to the Office of the Chief Engineer (DTD), Abhikshan, Sec-V, Salt Lake, Kolkata-91. The bidder will be given a receipt, jointly signed by the bidder and DTD officials, mentioning the samples and papers submitted by the bidder as per check list.

While submitting the samples and required documents as per Annexure-IV, the bidder shall submit three numbers of sealed meters as per the specifications stated herein before, two ultrasonic welded and one without welding and another dummy meter case (for checking ultrasonic welding).

They shall also submit one prototype of meter base and cover (with body screw caps) properly welded.

The date of testing of sample meters will be intimated to the bidders by CE (DTD) and during such test other bidders will also be allowed to witness the testing. Sample submission schedule and Test procedure may be changed due to emergency requirement. On the date of testing of sample meters of a particular bidder, he shall come prepared with the following.

BCS (as per specification)

CMRI compatible with BCS and loaded with CMRI software and laptop compatible with BCS.

Modem and accessories for testing the remote meter reading.

Any other accessories required for observing the performance and capabilities of the meters.

QUALITY ASSURANCE PLAN: The design life of the meter shall be minimum 20 years and to prove the design life the firm shall have at least the following quality Assurance Plan.

The factory shall be completely dust proof.

The test rooms shall be temperature and humidity controlled as per relevant standards.

h
10/12/25

M
10/12/25

AP
10/12/25

AL
10.12.25

10.12.25

10/12/25

The test and calibrating equipment shall be automatic and all test equipment shall have their valid calibration certificates.

Meter will be tested (in case of lot test) in fully automatic test bench with ICT. No. human intervention will be allowed during test.

Power supplies used in test equipment shall be distortion free with sinusoidal wave forms and maintaining constant voltage, current and frequency as per the relevant standards.

THE CHECKS TO BE CARRIED OUT DURING MANUFACTURING OF THE METERS:

Meter frame dimensions tolerances shall be minimal.

The assembly of parts shall be done with the help of jigs and fixtures so that human errors are eliminated.

The meters shall be batch tested on automatic, computerized test bench and the results shall be printed directly without any human errors.

35.0 LAB FACILITY: The laboratory of manufacturer must be well equipped for testing of the meters. They must have computerized standard power source and standard equipment calibrated not later than a year (or as per standard practice).

MANUFACTURING ACTIVITIES:

All the materials, electronics and power components, ICs used in the manufacture of the meter shall be of highest quality and reputed make to ensure higher reliability, longer life and sustained accuracy. The manufacturer shall use Application Specific Integrated Circuit (ASIC) or Micro controller for metering functions.

The electronic components shall be mounted on the printed circuit board using latest Surface Mounted Technology (SMT) except power components by deploying automatic SMT pick and place machine and re flow solder process. The electronic components used in the meter shall be of high quality and there shall be no drift in the accuracy of the meter at least up to 10 years.

Further, the Bidder shall own or have assured access (through hire, lease or sub-contract) of the mentioned facilities. The PCB material shall be of glass epoxy FR-4 grade conforming to relevant standards.

All insulating materials used in the construction of meters shall be non-hygroscopic, non-ageing and tested quality. All parts that likely to develop corrosion shall be effectively protected against corrosion by providing suitable protective coating. Quality shall be ensured at the following stages.

At PCB manufacturing stage, each board shall be subjected to bare board testing.

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

At insertion stage, all components shall undergo testing for conforming to design parameters and orientation. Complete assembled and soldered PCB shall undergo functional testing using test equipment (testing jig).

Prior to final testing and calibration, all meters shall be subjected to accelerated ageing test to eliminate infant mortality, i.e., meters are to be kept in ovens for 72 hours at 55 deg Centigrade temperature & atmospheric humid condition. After 72 hours meters shall work correctly. Facilities / arrangement for conducting ageing test shall be available with the manufacturer.

The calibration of meters shall be done in-house.

DOCUMENTATION:

Twenty sets of operating manuals shall be supplied to the office of the CE (DTD) for distribution at sites.

One set of routine test certificates shall accompany each dispatch consignment.

The acceptance test certificates in case pre-dispatch inspection or a routine test certificate in cases where inspection is waived shall be approved by the purchaser.

GUARANTEE:

The Meters shall be guaranteed arising out of faulty design, materials, bad workmanship for a period of **5½ years** from the date of supply.

39.0 REPLACEMENT OF DEFECTIVE METERS: The meters declared defective within the above guarantee period by the WBSEDCL shall be replaced by the supplier up to the full satisfaction of the WBSEDCL at the cost of supplier within one month on receipt of intimation. Failure to do so within the time limit prescribed shall lead to imposition of penalty of twice the cost of meter. The same may lead to black listing even, as decided by WBSEDCL. In this connection the decision of WBSEDCL shall be final.

PACKING & FORWARDING:

The energy meters shall have to be securely packed in transportable lots. If the energy meters are found acceptable after inspection and testing, the same shall have to be suitably sealed by the Inspecting Officer. Due care shall have to be ensured during transportation to keep the packing and seals intact for acceptance by consignee stores.

The equipment shall be packed in cartons / crates suitable for vertical / horizontal transport as the Case may be, and suitable to withstand handling during transport and outdoor storage during transit. The supplier shall be responsible for any damage to the equipment during transit, due to improper and inadequate packing. The easily

10/12

10/12/15

10/12/15

10.12.15

10/12/15

damageable material shall be carefully packed and marked with the appropriate caution symbol. Wherever necessary, proper arrangement for lifting, such as lifting hooks etc., shall be provided. Supplier without any extra cost shall supply any material found short inside the packing cases immediately.

The packing shall be done as per the standard practice as mentioned in IS 15707: 2006. Each package shall clearly indicate the marking details (for e.g, manufacturer's name, Sl. Nos. of meters in the package, quantity of meter, and other details as per supply order). However, the supplier shall ensure the packing is such that, the material shall not get damaged during transit.

Delivery :

Delivery of the meters shall be made only after receipt of the Dispatch Instruction (DI) to be issued by the Chief Engineer (DTD) upon approval of the supplier's test reports. The supplier shall send intimation regarding dispatch of the meters to the Offices of the Chief Engineer (P&C) and Chief Engineer (DTD), WBSEDCL immediately after dispatch of the consignment. Prior to dispatch of the consignment the supplier shall intimate the consignee duly so that consignee can acknowledge receipt of information.

The equipment/materials are to be delivered as per "Delivery Schedule" clause given hereunder. Allotment of serial number of meters will be available from the Distribution Testing Department, Abhikshan, WBSEDCL, Salt Lake, Kolkata-91, on any working day after issuance of this order upon receipt of written requisition for the same.

The materials shall reach the destination stores within 21 (twenty one) working days from the date of issue of the Dispatch Instruction (DI). Failure to do so for reasons, solely attributable to the supplier, shall attract LD as per relevant clause of this order.

Delay in offer beyond the Delivery Schedule for reasons solely attributable to the supplier shall attract imposition of LD as per relevant clause of this order.

In case the inspected materials are not delivered within one month after the stipulated period specified in the order without any valid reason the Dispatch Instruction (DI) already issued against the said lot shall be considered to be withdrawn.

Delivery of the meters shall be made only after receipt of the Dispatch Instruction (DI) to be issued by the Chief Engineer (DTD) upon approval of the supplier's test reports. The supplier shall send intimation regarding dispatch of the meters to the Offices of the Chief Engineer (P&C) and Chief Engineer (DTD), WBSEDCL immediately after dispatch of the consignment. Prior to dispatch of the consignment the supplier shall intimate the consignee duly so that consignee can acknowledge receipt of information.

100 no. of "Meter to PC" cords (having USB port with MOXA converter) shall be supplied to the Office of the Chief Engineer (DTD).

[Handwritten signatures and dates: 10/2/15, 10/2/15, 10/2/15, 10/2/15, 10/2/15]

42.0 Checking of Materials/Equipment after delivery :

The materials delivered to the consignee stores will be subjected to re-inspection/re-testing in presence of authorized representative of suppliers for which due notice in advance will be furnished by the Chief Engineer(DTD). If any discrepancy/dispute in quality arises in any sample selected from a lot, the supplier shall have to replace the entire lot at the supplier's cost and WBSEDCL reserves the right to take any penal action whatsoever without any further reference.

Inspection after receipt at stores:

WBSEDCL shall carry out acceptance testing of the supplied meters (collected from consignee stores) at their laboratory against DI of inspected lot. Advance intimation will be given to local representatives of the supplier over telephone. Such testing of the meters will be commenced within 10 days and completed within 20 days from the date of receipt of meters at consignee stores.


Acceptance Test as per "Inspection & Testing" clause of this order except dry heat test & shunt test will be conducted at the laboratory of Distribution Testing Department or any Zonal Testing Unit on sample meters selected from meters delivered at consignee stores. Sampling procedure will be followed as per relevant Indian Standards. Date of testing will be intimated to the suppliers and testing can be witnessed by authorized representatives of the suppliers. In case, the authorized representatives are not present, WBSEDCL shall test the meters unilaterally and the results obtained during testing will be binding on the suppliers.

In case the meters are found "Not In Order" as per observation during inspection and testing of the offered lot, the lot will be declared defective and in that event meters supplied are to be replaced by the manufacturers free of cost including free transportation from the site to their works and back. Before delivery of the replaced meters Acceptance Test shall be conducted by the supplier as per "Inspection and Testing" clause of this order in presence of WBSEDCL- representatives. Only if the test results are found to be satisfactory, replaced meters shall be allowed to be delivered.

Submission of report against defective meters


After delivery of the meters, if any defect is detected by the Testing Engineer / Site Office Personnel, the same will be intimated to the supplier. After getting intimation, the supplier shall send their competent personnel to the consignee store to set right the problem with an intimation to Distribution Testing Department (DTD) and to the Consignee. In case of minor defect, which can be set right at site, the same shall be taken up by the supplier without affecting the movement of the consignee store, failing which the meters are to be lifted from the consignee store for necessary rectification. If the detected defect is beyond repair, the meters are to be replaced


10/12


10/12/25


10/12/25


10.2.25


10/04/25

by newly tested meters and the defective meters will be handed over to the supplier by the consignee store. The replaced meters are to be sent to concerned Zonal Testing unit or DTD, Abhikshan for further testing.

The meter serial numbers for the meters, replaced against defective meters, shall bear numbers from the rolling stock serial numbers allotted by DTD against this order.

Regarding these defective meters, the supplier shall submit a report to DTD mentioning nature of defects (like, fault at current element / potential divider / SMPS / Computing Chip / Communication Module/ Display Module / NVM Module / Battery) against meter serial number. A format in this regard shall be provided by DTD duly.

45.0 Consignee : To be intimated by the Chief Engineer (DTD), Abhikshan, WBSEDCL, Kolkata - 700091 through the Dispatch Instructions (DI).

Calibration of measuring Instruments/Equipment used during inspection & testing : The instruments/equipment required for Inspection & Testing shall have valid calibration as per following guideline:

Calibration Certificate issued by Laboratory accredited by NABL, may be accepted unconditionally provided the certificate bears an accreditation body logo. For testing equipment, where NABL accreditation is not available, calibration certificate from Educational Institutions like IITs, NITs, JU, CU, BHU, only can be accepted provided traceability can be ascertained.

Necessary confirmation regarding above is to be given along with inspection offer failing which the inspection offer will not be accepted.

If during inspection & testing the supplier fails to produce Calibration Certificate as indicated above the offered lot may be rejected.

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

[Handwritten signature]
10/2/25

TAMPER LOGIC

Sl. No.	TAMPERS	Occurrence Condition	Restoration Conditions	Occurrence Time (Min/Sec)	Restoration Time (Min/Sec)
	Power Failure	When Power is OFF.	When Power is ON.	5 min.	Immediate
A	Import Mode:				
1	Invalid Voltage	$V_{3x} > 60\% V_{ref} \text{ \& } < 115\% V_{ref}$	$V_{3x} > 60\% V_{ref} \text{ \& } < 115\% V_{ref}$	5 min.	5 min.
		Angle difference of any twophases $< \pm 10^\circ$	Angle difference of any twophases $> \pm 10^\circ$		
2	Missing Potential	Any $V_x < 30\% V_{ref}$	Any $V_x > 40\% V_{ref}$	5 min.	5 min.
		Missing Potential detection will be Phase wise			
3	High Voltage	Any $V_x > 115\% V_{ref}$	$V_{3x} < 115\% V_{ref}$	5 min.	5 min.
		Current ignored	Current ignored		
4	Voltage Unbalance	$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$	$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$	5 min.	5 min.
		$(V_{max} - V_{min}) > 30\% V_{ref}$	$(V_{max} - V_{min}) < 30\% V_{ref}$		
5	CT Open	$I_{Residual} > 10\% I_b$	$I_{Residual} < 10\% I_b$	5 min.	5 min.
		$I_x < 2\% I_b$	$I_x > 2\% I_b$		
		Average line Current :Ignored	Average Phase Current $> 10\% I_b$		
		$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$	$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$		
		CT open detection will be phase wise			
6	CT Bypass	$I_{Residual} > 10\% I_b$	$I_{Residual} < 10\% I_b$	5 min.	5 min.
		$I_{3x} > 2\% I_b$	Phase Current Ignored		
		Average line Current :Ignored	Average Current $> 10\% I_b$		
		$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$	$V_{3x} > 70\% V_{ref} \text{ \& } < 115\% V_{ref}$		

Handwritten signature

Handwritten signature

Handwritten signature

Handwritten signature

Handwritten signature

7	Over current	Any $I_x > 110\% I_{max}$	$I_{3x} < 110\% I_{max}$	5 min.	5 min.
		$V_{3x} > 70\% V_{ref} \ \& \ < 115\% V_{ref}$	$V_{3x} > 70\% V_{ref} \ \& \ < 115\% V_{ref}$		
8	Low PF	$I_{3x} > 10\% I_b$	$I_{3x} > 10\% I_b$	5 min.	5 min.
		Average PF < 0.3	Average PF > 0.3		
		$V_{3x} > 70\% V_{ref} \ \& \ < 115\% V_{ref}$	$V_{3x} > 70\% V_{ref} \ \& \ < 115\% V_{ref}$		
9	Neutral Disturbance	<p>Bidders Logic</p> <p>If meter detects Neutral Disturbance tamper in "Export" mode, the energy increment shall be made in Import mode as per V_{ref}, Actual current and UPF.</p>	<p>Bidders Logic</p>	within 40 Secs	within 40 Secs
10	Voltage THD	When Voltage THD $> 8\%$ in any phase	When Voltage THD $< 8\%$ in all phases	5 min	5 min
11	Current THD	When Current THD $> 8\%$ in any phase	When Current THD $< 8\%$ in all phases	5 min	5 min
12	Magnet	Whenever the Meter functionality gets affected on account of presence of any magnetic field, meter shall log it as an event and start recording at I_{max} if does not remain immune. In Tamper Snap Shot I_{max} must be shown (either occurrence or restoration), with Date and Time stamp. If meter detects magnetic tamper in "Export" mode, the energy increment shall be made in Import mode as per V_{ref} , I_{max} and UPF.		within 40 Secs	within 40 Secs
13	Cover Open	On removal of meter cover the meter will log cover open event along with date and time	No restoration	Immediate	
B	Export Mode				
	Neutral Disturbance and Magnet	In Export Mode, meter recording must not start at I_{max} . Under any circumstances, if meter logs Neutral Disturbance or Magnetic Field Tamper event it will log in Import Register instead of Export Register.		Bidders Choice	

	Manual Resetting of Maximum Demand:	When Reset Button is pressed within an Integration Period, Rising Demand will not reset to Zero. The Demand will be registered for the entire Integration Period and will be logged as Current Max. Demand at the end of the Integration Period.	
<p>Please note:</p> <p>V_{3x} = Voltage in all Phases</p> <p>V_x = Voltage In any Phase</p> <p>I_{3x} = Current in all Phases</p> <p>I_x = Current in any phase</p>			

hwy
10/2

hwy
10/2/25

hwy
10/2/25

hwy
10/2/25

hwy
10/2/25

**Annexure-I
GTP for Meter**

Sl.No.	Item Description	Manufacturer's Particulars
1.	Maker's name and country	To be specified by the Bidder
2.	Type of meter/model	To be specified by the Bidder
3.	Standard Applicable	IS 14697, IS 15959, CBIP 325
4.	Accuracy/Interface class	0.5S
5.	Parameters displayed	As per Specification
6.	P.F. Range	Zero lag – unity – Zero Lead
7.	Basic Current (I _b)	5A, CTR 200/5A
8.	Maximum Current (I _{max})	10A
9.	Minimum starting current	0.1% of I _b -basic
10.	Rated Voltage	415 V : Phase to Phase, 240 V : Phase to Neutral
11.	Meter Constant	To be specified by the Bidder
12.	Variation of voltage at which meter functions normally	70% to 120% of reference Voltage
13.	Rated Frequency	50Hz±5%
14.	Power Loss in Voltage circuit (VA & watt) & Current circuits (VA)	Voltage Circuit :- Will not exceed 1.5W and 10VA per phase Current Circuit:- Will not exceed 1.0 VA per Phase
15.	Dynamic range	As per IS 14697
16.	MD reset Provisions	Possible to reset MD by any of the following options:- 1. Remote MD reset 2. Manual MD reset 3. MD reset by HHU 4. Auto Monthly Reset
17.	Display: a) Type of register b) No. of digit of display and height of character c) Auto display mode & scroll mode d) Type of push button for scroll mode	Display will be a) LCD b) 7 digit 7 segment, height- 10x5mm c) As per approved sample d) Spring loaded push button
18.	Non volatile memory	To be provided as per Specification
19.	Details of provision for taking reading during power off condition	Through internal non rechargeable battery
20.	Principle of operation	As per technical Specification
21.	MD integration period	15 minutes
22.	Weight of meter	To be specified by the Bidder
23.	Dimensions	To be specified by the Bidder
24.	Warranty	5 ½ years from the date of supply
25.	Outline drawings & leaflets	To be provided by the Bidder

[Handwritten signatures and dates are present at the bottom of the page, including dates like 10/2/25 and 10/1/25.]

Sl.No.	Item Description	Manufacturer's Particulars
26.	a) Remote meter- readout facility	Provision required
	b) Communication protocol used	DLMS
	c) Sealing provision for meter & optical port	To be provided as per Specification
	d) Baud rate of data transmission	9600 bps
	e) Required software to be resident in CMRI and BCS	To be provided by the Bidder
	f) Ultrasonic welding of body or any other technology which is equally or more efficacious	To be provided
	g) Manufacture Seal	To be provided
27.	Base Computer software	Compatible with windows 7 as well as latest windows version.
28.	Type test certificates	To be provided by the Bidder
29.	Time of day zones (selectable)	3 TOD Zones to be provided with a provision for 8 TOD Zones
30.	Whether meter measures both fundamental & harmonic energy	As per Specification
31.	Real time clock accuracy	Maximum drift ± 5 Minutes per annum.
32.	Battery for real time clock	It shall be Lithium-ion / Lithium battery having at least 10 years of life
33.	Anti tamper features	As per Tamper logic provided by WBSEDCL.
34.	Effect of accuracy under tamper conditions	As per technical specification
35.	Drift in accuracy of measurement with Time	As per IS: 14697 & CBIP 325.
36.	Name plate details	As per specification
37.	Type of calibration	Software calibrated
38.	Type of mounting	Projection mounting
39.	Testing facility	Shall be available with manufacturer, details to be provided
40.	Data retention by NVM without battery backup and un-powered condition	As per specification
41.	Type of material used:	
a.	Base	As per specification
b.	Cover	As per specification
c.	Terminal block	As per specification
d.	Terminal cover	As per specification
42.	Screw	
	i. Material	As per specification
	ii. Size	As per specification
43.	Internal diameter of terminal hole	5.5mm
44.	Centre to centre clearances between adjacent terminals	As per IS: 14697
45.	Security profiles	
	a) Basic Security	To be provided
	b) Advance security	To be provided

Specification for 3ph 4wire 240V LT CT Import-Export meter of Class 0.5S accuracy

Page 31 of 33

[Signature]
14/2

[Signature]
10/2/25

[Signature]
10/2/25

[Signature]
10.2.25

[Signature]
10/2/25

Annexure - II
Pre-Qualification Conditions for Three Phase Static Meters

Sl. No.	Particulars	Remarks
1	Bidders must have valid BIS certification for the offered meter.	Yes / No
2	Bidder preferably posses ISO 9001 certification	Yes / No
3	Bidder shall be manufacturers of static meters having supplied Static 1-ph or 3-phase meters with memory and LCD display to Electricity Boards / Utilities in the past 2 years	Yes / No
4	Bidder has Type Test certificate for the Type of offered meter not more than 3 (three) years old	Yes / No
5	Bidders shall have dust free, static protected environment for manufacture, assembly and Testing.	Yes / No
6	Bidder shall have automatic computerized test bench for lot testing of meters.	Yes / No
7	Bidder has facilities of Oven for ageing test.	Yes / No
8	Bidder shall submit certificate for immunity against magnetic influence of 0.2T DC, 67mT DC and 10mT AC and 0.5mT AC Magnetic field (as per CBIP 325) . from a NABL accredited Laboratory, for the same type of meter as offered.	Yes / No

Annexure – III

Sl. No.	Component Function / Feature	As per Requirement	Make / origin
1	Current Element		
2	Measurement / Computing chips		
3	Memory chips		
4	Display modules		
5	Communication modules		
6	Optical port		
7	Power Supply		
8	Electronic Components		
9	Mechanical parts		
10	Battery		
11	RTC / Micro controller		

Handwritten signature
10/2/25

Handwritten signature
10/2/25

Handwritten signature
10.2.25

Handwritten signature
10.2.25
10/02/25

ANNEXURE – IV

Sl. No.	LIST OF DOCUMENTS TO BE SUBMITTED DURING SAMPLE SUBMISSION			
1	Attested copy of type test reports from NABL accredited laboratory			
2	Attested copy of BIS certificates of the same type of meter submitted as sample			
3	Attested certificates as regards material used for meter case, cover & terminal block.			
4	Annexure – II as per tender documents			
5	Annexure – III as per tender documents			
6	Operating manual of the meter submitted			

[Signature]
10/12/25

[Signature]
10/12/25

[Signature]
10/12/25

[Signature]
10/12/25

[Signature]
10.2.25

[Signature]
10/12/25